

**ALARM SWITCHES AND SECURITY DEVICES
FOR COIN COLLECTORS/TELEPHONES
IDENTIFICATION AND INSTALLATION**

1. GENERAL

1.001 This addendum supplements Section 506-110-103, Issue 1.

1.002 This addendum is issued to revise the method of securing an armored cord in the backplate of a coin collector.

The following change applies to Part 3 of the section.

(a) 3.38 (10)—revised

(10) A P-26E084 1/4-20 by 5/16-inch self-locking setscrew is used to secure the cord to the coin collector backplate (Fig. 29). A flat surface is located approximately 1/4-inch from the set end of the stainless steel flexible hose. Using a 1/8-inch Allen wrench, screw the socket setscrew into the hole drilled in step 5 until it just makes contact with the flat surface of the metal hose. Give the setscrew a minimum of 1/4 turn and a maximum of 1/2 turn. This should hold the cord firmly in the coin collector.