

RINGER CONNECTIONS
TIP-PARTY IDENTIFICATION
FOR STATIONS CONNECTED TO LONG-LINE EQUIPMENT

1.00 GENERAL

1.01 Ringer leads must be reversed at 2-party tip stations with ground identification when these stations are connected to a long line circuit. This prevents bell tap. To do this, reverse all four ringer leads. This is necessary to prevent losing the proper tip-party identification. A typical example of these connections is shown in Table A.

TABLE A

RINGER CONNECTIONS OF 500C, D TELEPHONE SETS

1000 Ω IDFY GRD			2650 Ω IDFY GRD		
Ringer Lead	From	To	Ringer Lead	From	To
S-R	B	K	S-R	G	B
R	K	B	R	B	G
BK	G	B	BK	B	K
S	B	G	S	K	B

1.02 This information will be included in the following sections when they are reissued:

- | | |
|-------------|-------------|
| 502-200-403 | 502-510-410 |
| 502-200-404 | 502-510-404 |
| 502-400-402 | 502-510-406 |
| 502-400-409 | 502-510-407 |
| 502-400-410 | 502-510-408 |
| 502-510-400 | 502-520-402 |
| 502-510-401 | 502-520-404 |
| 502-520-406 | 502-410-400 |
| 502-520-400 | 502-560-400 |